

TOSHIBA DK40, DK40i, DK280 & DK424 QUICK REFERENCE VOICE MAIL INSTRUCTIONS

. How to activate your personal voice mail box

- . Press flashing MSG button and follow the instructions given by the Toshiba Tutorial

. How to check new voice mail messages from your own phone MSG light flashing

- . Press MSG button
- . Enter your security code and press #
- . Follow the system prompts

. How to check saved voice mail messages

- . Press Intercom button
- . Press 850
- . Press *
- . Enter your security code and press #
- . Follow the system prompts

. How to check your voice mail messages from outside the building

- . Call the main number (or the Back Door Number if applicable) and ask to be transferred to the voice mail
- . When you hear the System Announcement
- . Press *
- . Enter your mail box number and press #
- . Enter your security code and press #
- . Follow the system prompts

. How to change your personal greeting in your voice mail box

- . Press Intercom button
- . Press 850
- . Press *
- . Enter your mail box number and press #
- . Enter your security code and press #
- . Wait 5 seconds
- . Press 3
- . Press 1
- . Press 1 (Greeting 1)
- . Follow the system prompts and record your greeting

Toshiba DK40, DK40i, DK280 & DK424 Quick Reference Voice Mail Instructions
How to record Auto Attendant Greeting (Mail Box 990 – Security Code 990 – Greeting 1)

- . Press Intercom button
- . Press 850
- . Press *
- . Enter user ID (990) and #
- . Enter security code (990) and #
- . Press 3
- . Press 1
- . Press 1
- . Press 1 (to listen to your old greeting) or press 2 to record a new greeting
- . Record greeting “Thank You For Calling Valley Joist” and press # when finished

How to record Auto Attendant Instructions (Mail Box 991 – Security Code 991- Greeting 1 (Day) & Greeting 2 (Night)

- . Press Intercom button
- . Press 850
- . Press *
- . Enter user ID (991) and #
- . Enter security code (991) and #
- . Press 3
- . Press 1
- . Press 1 (Greeting 1 = day – Greeting 2 = night)
- . Press 1 (to listen to your old instructions) or press 2 to record a new instructions
- . Record instructions “If You Know The Extension Dial It Now - - - - -” and press # when finished